

8 Zone Paing Microphone Station



TECNARE
SOUND SYSTEMS

8 ZONE Remote Microphone Station for DMA8X8

- ▶ Controls
 - Zone selector switches for Z1~Z8. Talk & Chime on/of.
 - User selectable zone group switches for M1~M4.
 - Level control volume for MIC & Chime.
- ▶ Connectors
 - RS485 communication with DMA8X8.
 - DC input.
- ▶ Indicators
 - Power, Busy, Signal, Clip.

MODEL	MIC DMA8X8
Rated Output Level / Impedance	0dB / 600 Ω Balanced
Input sensitivity / Impedance	-36dB / 20k Ω Balanced
Frequency Response (-1dB)	80Hz - 15kHz
T.H.D	< 0.1%
Hum & Noise	> 90 dB
Number of Zone	8 Zones
Weight (Net)	1.2 kg
Dimensions (W x H x D)	140 x 60 x 205mm (only body)